COIN TIMER 24V, for showers

(Art.224)

TIMER FOR COINS OR TOKENS

When the use of time for showers has to be paid by coins or

TECHNICAL DATA

- The COIN TIMER 24V is useful when the use of time for showers has to be paid by coins or tokens. It is possible set up to a maximum time of 6 minutes.
- The COIN TIMER 24V has to be supplied with a voltage of 24Vac or 24Vdc, the same used to drive the solenoid valve that controls the water supply. In this way comes carried out a wiring with a safety extra-low voltage, that avoids
- the danger of electric shocks.

 The **COIN TIMER24V** comes with a strong metal container painted to dust and wall fixing. It has two doors both provided with locks. By the highest door it is possible to gain to the coin acceptor and the timer regulation (from 0 to 6 minutes). By the lowest door is gained access to the drawer that picks up the coins (or tokens) inserted. We recommend to install the COIN TIMER24V on the appropriate waiting shower-bath or however in a place where the COIN TIMER24V non-being liable for sprinklings of water.
- Power supply: 24Vac or 24Vdc ±10%.
 Output load: The output voltage will be the same of power supply.
- Maximum load: 5A (Ohmic load).
- Dimensions: width 15.3cm height 33.3cm depth 18.0cm.
- Weight: 4.1kg.

Available versions (selectable during purchase)

- Mechanical coin validator for 1 coin of:
 - **♦€** 0.50
 - **♦€ 1.00**
 - **♦€ 2.00**
- Mechanical tokens validator for 1 token

For the version with token acceptor, please specify the quantity of desired tokens (Art.R200-1).





Art.224# Product out of production #.....COIN TIMER-24V Size: 33,3x15,3x18cm. - Weight: 4.1kg.



Art.R200-1 TOKEN 26-1SS type Weight: 0.007kg.