

## PLAY30C-FENCING (Art.845)

Repeater panel for FENCING (75x59cm)

---

### Functioning:

It is used in the fencing matches, it repeats the **FULL-ARM-05** mains indications to allow their visibility to a longer distance; it is connected to a serial output of them by telephonic cable in endowment, long 15m but extensible till 100m.

---

### Displayed functions:

- **Scorer:** from 0 to 99 each side, 17.4cm of digits height, visible up to 50m and beyond.
  - **Yellow tag:** yellow bright dot on both sides.
  - **Priority:** 'P' letter on each side.
  - **Chronometer:** maximum time of 9 minutes and 59 seconds. 15cm of digits height, visibility up to 40m and above. The color of two bright points between minutes and seconds shows in a clear and immediate way the timer status: GREEN=counting, RED=stopped.
- 

### Technical data:

- **Installation:** Very simple because, after to have inserted the power plug and connected the **FULL-ARM-05**, the scoreboard is ready to use.
- **Cabinet:** Strong metal container, black dust painted. Transparent and antireflex front panel.
- **Dimensions:** width 75cm, height 59cm, depth 10cm.
- **Weight:** 13kg.
- **Serial cable length:** 15m.
- **Power supply:** 230Vac, 60VA max. It is also available the 115V version, selectable during purchase.



Art.845

**PLAY30-C/FENCING**

Size: 75x59x10cm. - Weight: 10.1kg.